

## Introduction

Thank you for purchasing Gerbing's Li-ion Battery models B7V-2500 battery. Please read the entire user manual prior to use.

Gerbing's Li-ion Battery is a slim and lightweight external battery pack that will allow you to power a variety of our heated products.

## Features

- Ultra-lightweight construction reduces bulk and weight
- LED battery level indicators
- LED power setting indicators
- Battery provides 2,500 mah of power

## NOTE:

*Failure to charge battery prior to use will reduce battery life.*

### **CHARGE BATTERY REGULARLY**

*It is important to maintain at least 25% of your battery power when not in use. Failure to do this will result in performance problems and reduced battery life.*

*Be certain to use your battery with products with an amp rating less than the maximum capacity output rating for the battery. For instance, the Li-ion battery pack has a maximum capacity output rating of 2 amps and should not be used with heated products that draw more than 2 amps. Please check your products amp draw before connecting battery pack. Failure to do so can overheat the battery causing damage.*

## Disposal

Do not place in fire or incinerate

Do not dispose in refuse

**Recycle in accordance with local regulations**

## Safety Precautions

**Please read the following warnings carefully before using the B7V-5200 Li-ion battery.** Use the product correctly and according to the procedures described in this manual.

## WARNINGS

- Do not attempt to disassemble or alter any part of this product.
- Do not store below -4° F (-20° C) or above 140° F (60° C).
- Do not allow this product to have contact with water or other liquids. If water or other liquids enter the battery interior, immediately unplug the product from the battery. Continued use of the product may result in fire or an electrical shock.
- Do not place this product near a heat source or expose the battery to direct flame or heat, as the battery may explode.

## Prior to Use

**Please read the following warnings carefully before using the BATLI722 (R) or B7V-2500 Li-ion battery.** Use the product correctly and according to the procedures described in this manual.

## Charging the B7V-2500 battery

Please refer to Figure 1 to become familiar with all aspects of the B7V-2500

To set up the charging process, proceed as follows:

1. Locate the charger's case with the 110v input prongs.
2. Plug the charger into a properly rated AC outlet (110v).
3. Plug the charger output cable(s) into the battery's charging ports.
4. The battery power level indicator LED is green when it's fully charged or red if charging is needed.
5. Charge battery until the red LED on the charger is a green color and all four LEDs on the battery are illuminated. The battery is now fully charged.

### **Power Setting Push-button and Indicators**

The B7V-2500 battery packs are equipped with a POWER button that has two separate functions. One is to allow you to check the remaining power or charge in the battery pack and the other allows you to change your power level setting or output.

- The Power Level push-button indicator can only be activated when not connected to a product. The battery's LED lights will display the battery's current power level from 25% to 100%. 100% indicates a full charge. Push and hold POWER button to check battery strength.
- The Power Setting push-button indicator can only be activated while connected to a product. Push and hold POWER button to select your desired setting from 25% to 100% power output. The default setting is 100%.

### **Battery Specifications**

Rating: 7.4 volt

Capacity: 2500 mah

Charging: DC 8.4 volts 1200 mah

Charge Time: 3 - 6 hours\*

\*3 hours for one battery with charger Model # BATLI722CG

6 hours for two batteries on Model # BATLICGD

### **Warranty and Registration Information**

When you purchase this Gerbing's battery within the United States, the electrical components of the battery are warranted to be free from factory defects in materials and workmanship for 90 days from the date of the initial purchase.

If you have a warranty claim, please return the battery together with the original receipt to Gerbing's Heated Clothing for inspection. Gerbing's will repair without charge a battery found under normal use to be defective during the warranty period. If we determine that a battery covered by the warranty cannot be repaired, we will replace the battery. Please allow 4-6 weeks for repair or replacement. Shipping costs are the responsibility of the customer.

This limited warranty sets forth the complete liability and obligations of Gerbing's Heated Clothing, Inc. for breach of warranty.

This limited warranty does not cover repairs by third parties, rips, scratches, tears, and cracks from abnormal use or deterioration caused by ordinary wear and tear or exposure. It also does not cover damage caused by accident, abuse or improper cleaning or care.

THIS WARRANTY IS IN LIEU OF ANY AND ALL OTHER WARRANTIES, EXPRESS OR IMPLIED, INCLUDING THOSE OF FITNESS FOR A PARTICULAR PURPOSE AND MERCHANTABILITY.

GERBING'S HEATED CLOTHING, INC. SHALL NOT BE LIABLE FOR ANY DAMAGES DIRECTLY OR INDIRECTLY RELATED TO GERBING'S HEATED PRODUCTS INCLUDING WITHOUT LIMITATION ANY DAMAGES FOR INJURY TO PERSONS OR PROPERTY OCCURRING WHILE ANYONE IS WEARING A GERBING'S HEATED PRODUCT.

WITHOUT LIMITING THE FOREGOING, GERBING'S HEATED CLOTHING, INC. SHALL NOT BE LIABLE FOR LOSS OF USE, INCONVENIENCE, LOST TIME, COMMERCIAL LOSS OR OTHER INCIDENTAL OR CONSEQUENTIAL DAMAGES.

THE FOREGOING LIMITATIONS OF LIABILITY SHALL APPLY TO THE FULL EXTENT PERMITTED BY LAW.